

GenSet



MG 7000 I-KO



GEN SET S.p.a.

Via Stazione,5 - 27030 Villanova D' Ardenghi (Pavia) Italy

Tel. (+39) 0382-5091 - Fax (+39) 0382-509-244

E-mail: genset@genset.it - internet: [//www.genset.it](http://www.genset.it)

MG 7000 I-KO

PORTABLE SINGLE-PHASE POWER GENERATOR / OUTPUT POWER 6,6 KVA
SINGLE-PHASE / PETROL ENGINE 3000 RPM

Gen Set Features	<ul style="list-style-type: none"> + Low oil level cut out device + 1 x 32 A, 230 V - 50 Hz single-phase EEC socket protected by circuit breaker + Voltmeter + Hourmeter
Gen Set Options (available as factory options)	<ul style="list-style-type: none"> + Version with different voltages + 60 Hz version + Electric starting version
Accessories on Request	<ul style="list-style-type: none"> + Trolley: two-wheels and handles
Noise Level	+ Lwa 98 (73 dB a 7 m)
AC Generator 50 Hz	<ul style="list-style-type: none"> + Type: synchronous + Single-phase power (stand-by): 6,6 kVA - 230 V + Single-phase power (prime): 6 kVA - 230 V + Power Factor: $\cos \varphi$ 0,8
Petrol Engine 3000 rpm	<ul style="list-style-type: none"> + Type: Kohler CH15 - 1 cyl. - 15 HP (11 kWm) @ 3600 rpm - 426 cm³ + Fuel: petrol + Cooling system: air + Starting system: manual + Fuel tank capacity: 6 l + Fuel consumption @ 75%: 5,2 l/h
Other Features	<ul style="list-style-type: none"> + Insulation Class: H + Ambient temperature: 40 °C + Altitude: 1000 mt + Mechanical Protection: IP 23 + Dimensions (L x W x H): 815 x 570 x 577 mm + Dry weight: 95 kg

Generator set in designed to operate in ambient temperature up to 40 °C and 1000 mt altitude - For higher values of temperature and altitude please consult factory to check available power.